

To access matrix menu, press 2<sup>nd</sup> > Matrix

### Gauss-Jordan Elimination

#### General Steps for Using Gauss-Jordan

##### Completing Column 1

$$\text{---} \cdot R_1 \rightarrow R_1 \quad \left| \begin{array}{ccc|c} 1 & & & \\ & & & \\ & & & \end{array} \right|$$

$$\begin{array}{l} \text{---} \cdot R_1 + R_2 \rightarrow R_2 \\ \text{---} \cdot R_1 + R_3 \rightarrow R_3 \end{array} \quad \left| \begin{array}{ccc|c} 1 & & & \\ 0 & & & \\ 0 & & & \end{array} \right|$$

##### Completing Column 2:

$$\text{---} \cdot R_2 \rightarrow R_2 \quad \left| \begin{array}{ccc|c} 1 & & & \\ 0 & 1 & & \\ 0 & & & \end{array} \right|$$

$$\begin{array}{l} \text{---} \cdot R_2 + R_1 \rightarrow R_1 \\ \text{---} \cdot R_2 + R_3 \rightarrow R_3 \end{array} \quad \left| \begin{array}{ccc|c} 1 & 0 & & \\ 0 & 1 & & \\ 0 & 0 & & \end{array} \right|$$

##### Completing Column 3:

$$\text{---} \cdot R_3 \rightarrow R_3 \quad \left| \begin{array}{ccc|c} 1 & 0 & & \\ 0 & 1 & & \\ 0 & 0 & 1 & \end{array} \right|$$

$$\begin{array}{l} \text{---} \cdot R_3 + R_1 \rightarrow R_1 \\ \text{---} \cdot R_3 + R_2 \rightarrow R_2 \end{array} \quad \left| \begin{array}{ccc|c} 1 & 0 & 0 & \\ 0 & 1 & 0 & \\ 0 & 0 & 1 & \end{array} \right|$$

Tips for using Gauss-Jordan:

- To get 1's, use reciprocals
- To get 0's, use additive inverses
- Use row 1 to get zeroes in column 1.
- Use row 2 to get zeroes in column 2, and so on.

#### Three Possible Outcomes (Examples):

##### 1) One Solution:

$$\left| \begin{array}{ccc|c} 1 & 0 & 0 & 5 \\ 0 & 1 & 0 & 2 \\ 0 & 0 & 1 & 4 \end{array} \right|$$

$x = 5$ ,  $y = 2$ , and  $z = 4$ . The solution is  $(5, 2, 4)$ .

##### 2) Infinite Solutions (dependent system):

$$\left| \begin{array}{ccc|c} 1 & 0 & 2 & 3 \\ 0 & 1 & -3 & 4 \\ 0 & 0 & 0 & 0 \end{array} \right|$$

The equations are:

$$x + 2z = 3 \text{ and } y - 3z = 4$$

Solve for  $x$  and  $y$ :

$$x = 3 - 2z \text{ and } y = 4 + 3z$$

Thus, the solution is:

$(3 - 2z, 4 + 3z, z)$  with  $z = \text{any real number}$

##### 3) No Solution (inconsistent system):

$$\left| \begin{array}{ccc|c} 1 & 0 & 0 & 5 \\ 0 & 1 & 0 & 2 \\ 0 & 0 & 0 & 4 \end{array} \right|$$

Here, this matrix tells us that  $0 = 4$  which we know is false. Thus, there is no solution.

To access matrix menu, press 2<sup>nd</sup> > Matrix

**Example:**

Solve the system represented by the matrix: 
$$\left| \begin{array}{ccc|c} 3 & 4 & 2 & 1 \\ 1 & 2 & 3 & 4 \\ 2 & 3 & 1 & 4 \end{array} \right|$$

The first step is to get a 1 in the first row of the first column.

The second step is to get zeros in the remaining cells of the first column.

Since there is a 1 in the second row, we'll do a row swap.

We will do this by using additive inverses.

$$\text{rowSwap}([A], 1, 2) \rightarrow [A]$$

$$* \text{row} + (-3, [A], 1, 2) \rightarrow [A]$$

$$* \text{row} + (-2, [A], 1, 3) \rightarrow [A]$$

$$R_1 \xleftrightarrow{\text{SWAP}} R_2$$

$$-3R_1 + R_2 \xrightarrow{\text{YIELDS THE NEW}} R_2$$

$$-2R_1 + R_3 \xrightarrow{\text{YIELDS THE NEW}} R_3$$

$$\left| \begin{array}{ccc|c} 1 & 2 & 3 & 4 \\ 3 & 4 & 2 & 1 \\ 2 & 3 & 1 & 4 \end{array} \right|$$

$$\left| \begin{array}{ccc|c} 1 & 2 & 3 & 4 \\ 0 & -2 & -7 & -11 \\ 2 & 3 & 1 & 4 \end{array} \right|$$

$$\left| \begin{array}{ccc|c} 1 & 2 & 3 & 4 \\ 0 & -2 & -7 & -11 \\ 0 & -1 & -5 & -4 \end{array} \right|$$

Now that we are done with the first column, we move to the second column. The next step is to get a 1 in the second row of the second column.

We now get zeros in the remaining entries of column 2.

$$* \text{row}(-1/2, [A], 2) \rightarrow [A]$$

$$\text{row} + ([A], 2, 3) \rightarrow [A]$$

$$* \text{row} + (-2, [A], 2, 1) \rightarrow [A]$$

$$-\frac{1}{2}R_2 \xrightarrow{\text{YIELDS THE NEW}} R_2$$

$$R_2 + R_3 \xrightarrow{\text{YIELDS THE NEW}} R_3$$

$$-2R_2 + R_1 \xrightarrow{\text{YIELDS THE NEW}} R_1$$

$$\left| \begin{array}{ccc|c} 1 & 2 & 3 & 4 \\ 0 & 1 & 7/2 & 11/2 \\ 0 & -1 & -5 & -4 \end{array} \right|$$

$$\left| \begin{array}{ccc|c} 1 & 2 & 3 & 4 \\ 0 & 1 & 7/2 & 11/2 \\ 0 & 0 & -3/2 & 3/2 \end{array} \right|$$

$$\left| \begin{array}{ccc|c} 1 & 0 & -4 & -7 \\ 0 & 1 & 7/2 & 11/2 \\ 0 & 0 & -3/2 & 3/2 \end{array} \right|$$

Now that we are done with the second column, we move to the third column. We begin by getting a 1 in the third row.  $* \text{row}(-2/3, [A], 3) \rightarrow [A]$

Finally, we get zeros in the remaining entries of column 3.

$$* \text{row} + (-7/2, [A], 3, 2) \rightarrow [A]$$

$$* \text{row} + (4, [A], 3, 1) \rightarrow [A]$$

$$-\frac{2}{3}R_3 \xrightarrow{\text{YIELDS THE NEW}} R_3$$

$$-\frac{7}{2}R_3 + R_2 \xrightarrow{\text{YIELDS THE NEW}} R_2$$

$$4R_3 + R_1 \xrightarrow{\text{YIELDS THE NEW}} R_1$$

$$\left| \begin{array}{ccc|c} 1 & 0 & -4 & -7 \\ 0 & 1 & 7/2 & 11/2 \\ 0 & 0 & 1 & -1 \end{array} \right|$$

$$\left| \begin{array}{ccc|c} 1 & 0 & -4 & -7 \\ 0 & 1 & 0 & 9 \\ 0 & 0 & 1 & -1 \end{array} \right|$$

$$\left| \begin{array}{ccc|c} 1 & 0 & 0 & -11 \\ 0 & 1 & 0 & 9 \\ 0 & 0 & 1 & -1 \end{array} \right|$$